



3585C

Motion sensor, it controls one or more devices connected for light control. Infrared detection with angle of 140 ° Distance of the adjustable sensor from 2 to 8 m. Switch off delay with 1 to 30 min adjustable delay time and 1 to 1000 lux brightness threshold. Test possible with a 5 sec. delay Recommended assembly height: 2.5 m. Optimum distance between 2 detectors: 6 m. For indoor and outdoor use (IP44). Supplied with 2 x 1.5V AA batteries for power supply.

Technical features

Brand	BTicino
Rated voltage	2 pile da 1,5V tipo AA
Protection class	IP44
Height	114 mm
Width	77 mm
Depth	48,5 mm
Plant type	Radio
Illuminance level	5 a 1000 lux
Installation height	2,5 m
Operating temperature	+5 C + 45 °C
Connection type	Connected
Colour	White
Series	Living Now

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8005543672884

Technical documentation

? Instruction Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with

**N4411C**

Dimmer/switch. It allows to control ligh...

**NT4411C**

Dimmer/switch. It allows to control ligh...

**L4411C**

Dimmer/switch. It allows to control ligh...

**L4003C**

Connected two-way switch. It allows to c...

**NT4003C**

Connected two-way switch. It allows to c...

**N4003C**

Connected two-way switch. It allows to c...

**NT4500C**

Gateway. This pack enables to create a c...

**N4500C**

Gateway to create a connected installati...

**L4500C**

Gateway. This pack enables to create a c...

**FC80GT**

Smart DIN gateway for remote control via...