



375000

bticino

Guard station with 10" touch display and handset. From the touch display, it is possible to: answer and transfer calls, view call logs, release the locks, monitor IP cameras installed in common areas, monitor and process alarms. From the setting menu, it is possible to adjust the guard station settings, like volume and display brightness, and carry out functionality and network tests. Quick and scheduled absence can be activated to transfer the call to another guard station or to apartments if needed. The guard station can be PoE (power over Ethernet) powered, or directly powered using power supply BT-375005.

Technical features

Brand	BTicino
Rated voltage	24Vdc
Protection class	IP30
Height	165mm
Width	308mm
Length	211mm
Depth	170mm
Maximum cable section	0.8mm
Plant type	IP
insertion	RJ45
Operating temperature	-10° - +55°C
Colour	Silver
Series	IP Door Entry System

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8005543693551

Technical documentation

? Technical Data Sheet
 ? DWG drawing
 ? Technical Datasheet

? Instruction sheet
 ? Installer Manual

We, BTicino S.p.A. Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with



375005

Power supply 100 W with
metal box; can b...