

8005543556931





BMSA1204



Switch Sensor with passive infrared, for the movement detection and the level of illumination, "Zero Crossing" technology, ON/OFF and the level of illumination, "Zero Crossing" technology, ON/OFF management, flush mount in the ceiling with springs or box, surface installation, protection degree IP41, quick terminal connection, covering area diameter 8 m (50 mq) for an height of 2.5 m, maximum installation height 6 m, power supply 100-240 Vac, 50/60 Hz, maximum load 4.3 A at 230 Vac, luminance level setting by trimmer from 10 lux to 1275 lux and delay time from 10 s to 10 min

Technical features		Commercial data	
Brand	BTicino	Minimum quantity	2
Rated voltage	240Vac	Sales unit	2
Frequency	50-60Hz	EAN code	80
Contact type	4.3 A		
Protection class	IP41		
Depth	50.5mm		
Diameter	95 mm		
Illuminance level	10-1275 lux		
Colour	Bianco		
Series	Stand alone solutions for lighting management		

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The optimizance are be proved by Certificates is issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.