

BTICINO &gt; Low voltage energy distribution &gt; BTDIN miniature circuit breakers &gt; Motor protectors


**417300**

Motor protector 3P thermal-magnetic with lever command - Vn=690V - Ir=0.1-0.16A - Im= 2.1A - Icu= 100kA (a 415Vac) - Pw motor 0.02W. Standard compliance IEC 60947-1, IEC 60947-2, IEC 60947-4. Thermic trip unit settable. Magnetic trip unit fixed ad 13le max

## Technical features

Protection index	IP20
Max section	6mmq
Height	84mm
Width	46mm
Depth	76mm
N° of modules	2.5
Standard reference	CEI EN 60947-1/2/4
N° of poles	3P
Ultimate breaking capacity Icu	100kA
Rated voltage	690Vac
Rated current	0.1-0.16A
Series	Btdin

## Documentation

[Catalogue BTDIN](#)

## Related products



**417400**

Auxiliary contact 1NO+1NC for motor protector (max 2 contacts for motor protector). Mounting on the ...



**417406**

Alarm contact 1NO+1NC for motor protector. Report the trip of the motor protector in case of fault o...



**417411**

Shunt trip for motor protector  $V_n = 110\text{Vac} - 50\text{Hz} / 120\text{Vac} - 60\text{Hz}$ . Mounting on the right side of the ...



**417412**

Shunt trip for motor protector  $V_n = 220-230\text{Vac} - 50\text{Hz} / 240-260\text{Vac} - 60\text{Hz}$ . Mounting on the right side...



**417413**

Shunt trip for motor protector  $V_n = 380-400\text{Vac} - 50\text{Hz} / 440-460\text{Vac} - 60\text{Hz}$ . Mounting on the right side...



**417421**

Undervoltage release for motor protector  $V_n = 110\text{Vac} - 50\text{Hz} / 120\text{Vac} - 60\text{Hz}$ . Mounting on the right si...



**417422**

Undervoltage release for motor protector  $V_n = 220-230\text{Vac} - 50\text{Hz} / 240-260\text{Vac} - 60\text{Hz}$ . Mounting on the ...



**417423**

Undervoltage release for motor protector  $V_n = 380-400\text{Vac} - 50\text{Hz} / 440-460\text{Vac} - 60\text{Hz}$ . Mounting on the ...