



HS4411

bticino

Universal pushbutton dimmer (resistive, inductive, capacitive, fluorescent compact and dimmer LEDs) - supply range 100-240 V.a.c. - no neutral – 2 modules - anthracite - 240 V.Ac.: Incandescents and hologens 3 - 400 W; Halogens with ferromagnetic transformer 3 - 400 VA; Halogens with electronic transformer 3 - 400 VA; Dimmerable compact fluorescents 3 - 150 VA; Dimmerable LED lamps 3 - 150 VA. - 100 V.Ac.: Incandescents and hologens 3 - 200 W; Halogens with ferromagnetic transformer - 200 VA; Halogens with electronic transformer 3 - 200 VA; Dimmerable compact fluorescents 3 - 75 VA; Dimmerable LED lamps 3 - 75 VA.

Technical features

Brand	BTicino
Rated voltage	100-240Vac
Rated power (W)	20-600W
Rated power (VA)	20-600VA
Modules	2
Series	Axolute

Commercial data

Minimum quantity	6
Sales unit	6
EAN code	8005543486474

Technical documentation

? Instruction Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.