

346994



Universal speaker unit with built-in relay (for controlling an electric door lock), designed for the installation of the 2-WIRES audio system in both new and refurbished setups where “special” pushbutton panels are present or required (such as mailboxes, patterned brass, compact sheet metal units, etc.) that are pre-configured for a traditional speaker module (e.g., 2659N). The universal speaker unit includes terminals for connecting up to 4 call pushbuttons and 1 local door release pushbutton. For systems with more than 4 call pushbuttons, it is necessary to add item 346993, with 1 unit required for every 8 pushbuttons (up to a maximum of 100 pushbuttons). The multi-cable with 2 connectors supplied with item 346993 must be used for the connection. Microphone sensitivity and speaker volume can be adjusted using dedicated potentiometers. The microphone of the speaker unit can be detached and placed at a distance of up to 15 cm from the device. In video systems, the device must be paired with cameras featuring coaxial output using interface 347400.

Technical features

Brand	BTicino
Rated voltage	18-27Vdc
Dimensions	90x55x26mm
Height	55mm
Width	90mm
Depth	26mm
Operating temperature	(-25°)-(+50°)C
Series	2 wires system

Technical documentation

[? Instructions](#)
[? Technical sheet](#)

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 “R&TTE” or where requested also in compliance with 2014/53/EU: 16 April 2014 “RED”. BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with

**346993**

Sfera expander button module. Allows you...

**347400**

Interface for the conversion of the coax...