



## 373003



10" touch display premium indoor unit with SOS pushbutton. From the touch display, it is possible to answer the call, open the lock, call the other apartments and the guard station, view call and alarm logs, leave audio messages, receive messages from the guard station, adjust the settings (e.g. brightness, screensaver, backgrounds and ringtone) and view date/time information. Alarm management can be easily integrated thanks to 8 pre-arranged dedicated contacts. The integration with the Onvif IP cameras allows to view the IP cameras of the apartment and the common areas from the indoor unit. The specific integration also allows control of the lift. It is possible to associate the video indoor unit to the Home + Security App (available for Android and iOS). The App allows to use functions such as: receiving calls, door lock release, display of the event timeline and activation of the entrance panel. With the Home + Security App, it is also possible to manage the products of the Netatmo Security range (outdoor and indoor cameras, door and window sensors, indoor siren, smoke detector). This allows you to quickly and easily create a Smart security system. The indoor unit can be PoE (power over Ethernet) powered, or directly powered using power supply BT-375005. Wall mounted using the supplied bracket.

### Technical features

Brand	BTicino
Rated voltage	24Vdc
Protection class	IP30
Dimensions	186x280x28mm
Height	186mm
Width	280mm
Depth	28mm
Maximum cable section	0.8mm
Plant type	IP
insertion	RJ45
Robustness	IP30

Installation height 160-165cm

Operating temperature -10° - +55°C

Colour Silver

Series IP Door Entry System

## Commercial data

Minimum quantity 1

Sales unit 1

EAN code 8005543690963

## Technical documentation

? Technical Data Sheet

? DWG drawing

? Technical Datasheet

? Instruction sheet

? Installer Manual

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

## Complete with



**375005**

Power supply 100 W with metal box; can b...

## Alternative solutions

---



**373004**

7" touch display premium  
indoor unit wit...