





4411C

Livinglight, Living Now, Matix, Classia



Connected relè/dimmer micromodule with neutral. Used to connect lights with a ceiling box installation. Can be controlled by one or more wireless light switches and/or mechanical pushbuttons. Switch with dimmer option, 150 W LED, wired. For local or remote ON/OFF or dimming control of lighting. Dimmer mode can be activated from the Home + Control app. Memory level function. Compatible with all loads: - dimmable LEDs and CFL lamps: 150 W LED - Incandescent and halogen lamps: 150 W - ELV halogen and CFL lamps with separate ballast: 150 VA

Commercial data

	h 11 1 1 1 1	tootiiwoo
(-/ ·	11111(''211	TEATHER
	шиса	features

Brand	BTicino	Minimum quantity	1
Rated voltage	230Vac	Sales unit	1
Rated power (W)	150W	EAN code	800554372613
Rated power (VA)	150VA		
Modules	Basic		

Technical documentation

? Instruction Sheet

Series

? Technical Data Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.