



F422A

bticino

2 Din modules interface between SCS BUS based systems, dedicated just to the logic expansion of the address extension and not to all the functions supported with F422. It can be used with both, DIN server item F460 and video door entry Classe300EOS with Netatmo. Each interface can add 175 addresses, with a maximum of 2 interfaces allowed for installation (max 2 interfaces in installation with DIN server item F460 and max 1 interface with Classe300EOS with Netatmo as server). Thanks to this device you will be able to overcome the current limit of 175 addresses and configure huge installations with up to 525 addresses. No parameters to take into consideration because the assignment is automatic.

Technical features

Brand	BTicino
Rated voltage	18 – 27Vdc
Input current	8mA
Modules	2
Series	MyHome, Living Now, Livinglight, Matix

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8005543714959

Technical documentation

[? Technical Data Sheet](#)[? Instruction Sheet](#)[? DWG drawing](#)

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.