

## Distributed by BTicino GENERAL CATALOGUE



# FC80RC



DIN smart relay for light control with maximum absorption In = 16 A. Equipped with contacts for control with remote buttons, up to a maximum of 10. The smart relay allows the lights to be controlled locally and remotely through radio commands, wired buttons, smartphone with the "Home + Control" App or via a voice assistant. Dimensions 1 DIN module. Power supply 110-230 Va.c. 50/60 Hz.

### Technical features

Brand	BTicino	Minimum quantity	1
Rated voltage	100-240Vac	Sales unit	1
Input current	16A	EAN code	8005543647844
Modules	1		
Series	Btdin		

Commercial data

#### Technical documentation

- ? Instruction Sheet
- ? Instruction Sheet

? Technical Data Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1999 'R&CTTE'' or where requested also in compliance with 2014/53/EU: 16 April 2014 'RED''. BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

# Complete with







