



JW4418



Universal Pushbutton Dimmer - with neutral, 3 wires. Can be associated with one or several push-buttons (non illuminated type). Each push-button able to perform the On/Off and dimming function. Memory level function: Lights come on again at the same lighting level as before they were last switch-off. Lower and upper thresholds setting. Indicator/locator function. For all types of lamps: - Dimmable LEDs and CFLs : 0 to 150 W (15 lamps max.) - Halogen, incandescent 230 V~ : 0 to 150 W - Halogen with ferromagnetic or electronic transformer : 0 to 150 VA. Depth 35 mm (with neutral). Standby consumption < 5 mW. - 1 module - White

Technical features

| | |
|-----------------|--------------|
| Brand | BTicino |
| Rated voltage | 100 ÷ 240Vac |
| Frequency | 50 ÷ 60Hz |
| Rated power (W) | 75W - 150W |
| Modules | 1 |
| Series | MatixGO |

Commercial data

| | |
|------------------|---------------|
| Minimum quantity | 5 |
| Sales unit | 5 |
| EAN code | 8005543736500 |

Technical documentation

? [Technical Data Sheet](#)

? [Instruction sheet](#)

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/53/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.