



CE4TBDT MID UTF

IME

Conto D4-Pt MID - Energy meter, active MID (cl.B) and reactive (cl.2) Connection: via CT (5A) - UTF DC15 certification - Network: three-phase 4-wires unbalanced - Dimension: 4 DIN modules - Output: RS485 - Input (from CT) : 1A-5A - Voltage: 3x230/400V - Aux: self-supplied

Technical features

Brand	IME
Rated voltage	230-400Vac
Auxiliary	Autoalimentato / Self-supplied
Frequency	50-60Hz
Input current	1-5A
Modules	4
Protection class	IP20
Accuracy class	B
Input	Doppia tariffa o impulsi / Double tarif or pulse
Output	RS485 Modbus
Plant type	Trifase / three-phase
insertion	TA/TV / CT/VT
Series	

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8032826515651

Technical documentation

? DWG, DXG and STP drawings
? MODBUS protocol

? M-BUS protocol

We, BTicino S.p.A. Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with



CE4TBDTMID

Conto D4-Pt MID - Energy
meter, active M...