



MF6DC4206H

IME

Nemo D4-DC - Multifunction for application in DC with energy count - Display: LCD backlit - Dimension: 4 DIN modules - Output: 2 alarm relay+communication RS485, protocol JBUS/MODBUS - Current: 10A direct or by shunt 60 mV or 100 mV or 150mV - Input: 10÷300Vac - Auxiliary supply: 20÷150Vdc + 48Vac

Technical features

Brand	IME
Auxiliary	20-150Vdc/48Vac
Input current	10A
Modules	4
Protection class IP20	
Input	50-1500vac
Output	impulsi / pulse + 2 allarmi / alarm + RS485 ModBus
insertion	diretta fino a 10A / direct up to 10A
Series	

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8032826038464

Technical documentation

- ? Technical sheet
- ? Instruction manual

- ? Protocol

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with

**MF6DC4200H**Nemo D4-DC -
Multifunction for
applicati...**MF6DC42066**Nemo D4-DC -
Multifunction for
applicati...