



TASL10C500

IME

TAS65 - Current transformer, single-phase - Cable/passing bar:
32x65mm - Ratio: 500/1A - Class: 0.5/1 - Accuracy: 8/10VA

Technical features

Brand	IME
Input current	500/1A
Rated power (VA)	8/10VA
Accuracy class	0.5/1
Dimensions	32x65mm

Series

Commercial data

Minimum quantity	1
Sales unit	1
EAN code	8032826145216

Technical documentation

? Technical Data Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.

Complete with



TASL50C500
TAS65 - Current
transformer, single-phas...



TASL50C5003
TAS65 - Current
transformer, single-phas...



TASL10C5003
TAS65 - Current
transformer, single-phas...



ATACOP04
Terminal cover for
TAS65/TAS84/TAS102/TA...



ATADIS03
Profile for bars 50mm
TAS65...



ATAFIS01
Pair of wall fixing feet for
TAS65/TAS12...