



003546



KNX coupler, to be used for the bidirectional exchange of data between two KNX lines ensuring galvanic isolation. It can be used as: - line coupler (for coupling of one line to one main line) - backbone coupler (to couple a main line to backbone line) - repeater (for the coupling of two segments of the same line) For a detailed diagnosis, all operating modes / states are shown by 6 LEDs Double bus connection via red-black KNX connector. Supply voltage SELV 29 Vd.c. by bus KNX. Installation on DIN rail, dimensions 2 DIN modules

Technical features

| | |
|--------------------|---|
| Brand | Legrand |
| Reference Standard | EN 50090 - EN 13321-1 e ISO/IEC 14543-3 |
| Rated voltage | 29 Vd.c. |
| Input current | 10 mA |
| Modules | 2 DIN |
| Protection class | IP 20 e IK 04 |
| Plant type | KNX |
| Series | KNX |

Commercial data

| | |
|------------------|---------------|
| Minimum quantity | 1 |
| Sales unit | 1 |
| EAN code | 3414972052429 |

Technical documentation

? ETS Project File

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU; 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU; 26 February 2014, and/or where requested also in compliance with 1995/5/CE; 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU; 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.