



048778

legrand

PIR technology sensor for the activation of the "VIRTUAL KEY CARD" function. The VIRTUAL KEY CARD function gives the possibility of activating the functions inside the room through the detection of the presence of an individual in the room, without the need to use the key card switch. The sensor is stand-alone and is not connected to the SCS-BUS (power supply 8 - 30 Vdc); it also has a NO contact output (8 - 30 Vdc - max applicable voltage). Wall mounted or ceiling Installation, diameter 25 mm. When installed on the ceiling at a height of 2.5 m, it covers a range of 5 m

## Technical features

Brand	Legrand
Rated voltage	8-30Vdc
Input current	9mA
Contact type	1NO
Depth	50mm
Diameter	esterno 38mm - interno 24mm
Operating temperature	5 °C / + 45 °C
Colour	Bianco
Series	

## Commercial data

Minimum quantity	1
Sales unit	1
EAN code	3414971251816

## Technical documentation

? Instruction Sheet

We, BTicino S.p.A Viale Borri 231 21100 Varese (Italy), declare that all items listed in BTicino catalogues, have been manufactured in compliance with the principal elements of safety objectives of European Directive said LVD: 2014/35/EU: 26 February 2014 and, where requested, also in compliance with essential protection requirements of electromagnetic compatibility according to European Directive 2014/30/EU: 26 February 2014, and/or where requested also in compliance with 1995/5/CE: 9 March 1999 "R&TTE" or where requested also in compliance with 2014/53/EU: 16 April 2014 "RED". BTicino S.p.A. products are in compliance with the standard published by the International Electrotechnical Commission (IEC). The compliance can be proved by Certificates issued by organizations recognized by IEC according to the CB-scheme. Our items comply with relevant European Product- Standards and show, whether provided, CE marking, they have been constructed in accordance with good engineering practice in safety matters in force in the Community, they do not endanger the safety of persons, domestic animals or property when properly installed and maintained and used in applications for which they were made.